




AWMC-060-8P-8CH

8 Channels RGB IR Controller,
8 Programs & USB Programmable


- AWMC-060-8P-8CH is a 8 programs, 8 Channels IR remote controller for controlling RGB LED modules, it has 8 programs, each program has 66 steps
- AWMC-060-8P-8CH has the function of P-cycle, run from P1 to P8
- Via IR remote controller to set: Brightness, Speed of Color changing, Fade/Jump, Color memory, Program changing.
- Via USB to connect to computer, by **Color Edit mini** or **Color Edit** software to edit RGB programs.

Specification:

Model Number	AWMC-060-8P-8CH
*Power Supply Output Voltage	DC 24V/20A Output MAX 480W DC 12V/20A Output MAX 240W
LED module type	Constant voltage with constant current, or Constant voltage with limit voltage
Operating Temp.	0°C ~ +50°C
Storage Temp.	-10°C ~ +60°C




1.67 Million Colors



USB



Software



Remote Control